


Model Name : CIP-5300

| | |
|--|---|
| <p>Image</p> |  |
| <p>System Protocol</p> <ul style="list-style-type: none"> -ITU-T Recommendation H.323 Ver. 3.0 -IETA Recommendation SIP RFC3261 | <p>E-mail(optional)</p> <ul style="list-style-type: none"> -Send/ Receive E-mail -Send/Receive SMS(Short Message Service) -POP3,SMTP |
| <p>Network</p> <ul style="list-style-type: none"> -10/100Base-T -Support LAN,ADSL,CABLE Modem -Support PPP/PPPoE | <p>Web Browser(optional)</p> <ul style="list-style-type: none"> -Browse Web Sites and Contents with a built In cHTML Browser |
| <p>Video</p> <ul style="list-style-type: none"> -ITU-T Recommendation : H.263 -CIF Resolution : 352*288 pixels -QCIF Resolution : 176*144 pixels -Maximum Frame rate(CIF) : 30fps | <p>GUI</p> <ul style="list-style-type: none"> -User friendly Graphic User Interface |
| <p>Audio</p> <ul style="list-style-type: none"> -ITU-T Recommendation :G.723.1/711 -Frequency response : 50Hz~3.4KHz -Half Duplex | <p>Internet Protocols</p> <ul style="list-style-type: none"> -TCP/IP,UDP,ICMP,DHCP |
| <p>Camera</p> <ul style="list-style-type: none"> -1/3" built-in Analog COMS -Auto exposure and white balance | <p>Electrical</p> <ul style="list-style-type: none"> -Power Consumption(max) : 17W -Power Supply(AC Adaptor) : 110~240AC -Operation Voltage : +5V DC |
| <p>Display</p> <ul style="list-style-type: none"> -Active Matrix TFT LCD -SIZE : 3.5 inches -Resolution : 480*234 pixels | <p>Voice Encryption(optional)</p> <ul style="list-style-type: none"> -ITU-T Recommendation : H.235 -Security framework used to provide authentication and integrity to H.323 systems |

ANDA Telecom Pvt. Ltd.


Registered office : E-36, Amar Colony, Lajpat Nagar- IV, New Delhi – 110024, INDIA

Phone : +91 11 41323629, +91 93 502 57173

E-mail : Info@andatelecomindia.com

URL : www.andatelecomindia.com

Model Name : CIP-4500

| | |
|---|---|
| <p>Image</p> |  |
| <p>System Protocol</p> <ul style="list-style-type: none"> -ITU-T Recommendation H.323 Ver. 3.0 -IETA Recommendation SIP RFC3261 | <p>E-mail(optional)</p> <ul style="list-style-type: none"> -Send/ Receive E-mail -Send/Receive SMS(Short Message Service) -POP3,SMTP |
| <p>Network</p> <ul style="list-style-type: none"> -10/100Base-T -Support LAN,ADSL,CABLE Modem -Support PPP/PPPoE -Integrated Hub Function(2 RJ-45Ports) | <p>Web Browser(optional)</p> <ul style="list-style-type: none"> -Browse Web Sites and Contents with a built In cHTML Browser |
| <p>Video</p> <ul style="list-style-type: none"> -ITU-T Recommendation : H.263 -CIF Resolution : 352*288 pixels -QCIF Resolution : 176*144 pixels -Maximum Frame rate(CIF) : 30fps | <p>GUI</p> <ul style="list-style-type: none"> -User friendly Graphic User Interface |
| <p>Audio</p> <ul style="list-style-type: none"> -ITU-T Recommendation : G.723.1/711 -Frequency response : 50Hz~3.4KHz -Full Duplex | <p>Internet Protocols</p> <ul style="list-style-type: none"> -TCP/IP,UDP,ICMP,DHCP |
| <p>Camera</p> <ul style="list-style-type: none"> -Illumination(min) : 1.0lux(20IRE),F.2.0 -Horizontal field of view(max) : 50 -Vertical field of view(max) : 39 -Auto exposure and white balance | <p>Electrical</p> <ul style="list-style-type: none"> -Power Consumption(max) : 17W -Power Supply(AC Adaptor) : 110~240AC -Operation Voltage : +3.3V,+5V,+12V DC |
| | |
| <p>Display</p> <ul style="list-style-type: none"> -Active Matrix TFT LCD -SIZE : 4.05 inches | <p>Voice Encryption(optional)</p> <ul style="list-style-type: none"> -ITU-T Recommendation : H.235 -Security framework used to provide |

ANDA Telecom Pvt. Ltd.

Registered office : E-36, Amar Colony, Lajpat Nagar- IV, New Delhi – 110024, INDIA
 Phone : +91 11 41323629, +91 93 502 57173
 E-mail : Info@andatelecomindia.com URL : www.andatelecomindia.com



Turning Copper into Gold

-Resolution : 480*234 pixels

authentication and integrity to H.323 systems

ANANDA Telecom Pvt. Ltd.

Registered office : E-36, Amar Colony, Lajpat Nagar- IV, New Delhi – 110024, INDIA

Phone : +91 11 41323629, +91 93 502 57173

E-mail : Info@andatelecomindia.com

URL : www.andatelecomindia.com